

NATIONAL AERONAUTICS AND SPACE ADMINISTRATION

GEORGE C. MARSHALL SPACE FLIGHT CENTER

HUNTSVILLE, ALABAMA

June 24, 1964

RING COUPLED FILTER DEVELOPMENT

FINAL REPORT

CONTRACT NAS 8-11507

For the Period July, 1963 to 31 May, 1964

GPO PRICE \$ _____

OTS PRICE(S) \$ _____

Hard copy (HC) 3.00

Microfiche (MF) .75

FACILITY FORM 808	N65 13555	
	(ACCESSION NUMBER)	(THRU)
	65	1
	(PAGES)	(CODE)
	OK 5 9643	15
	(NASA CR OR TMX OR AD NUMBER)	(CATEGORY)

COLLINS RADIO COMPANY
R & D DIVISION B
19700 SAN JOAQUIN ROAD
NEWPORT BEACH, CALIFORNIA

D. L. BISE

TABLE OF CONTENTS

<u>SECTION</u>	<u>TITLE</u>	<u>PAGE</u>
1	Purpose	1
2	Abstract	2
3	Factual Data	3
4	Conclusions	8
5	Recommendations	9
6	Appendices	48

1. PURPOSE

A contract was issued to Collins Radio Company on July 1, 1963, by the George C. Marshall Space Flight Center to determine the practicability of building narrow bandwidth ring coupled mechanical filters employing integral disk-ring elements.

To accomplish the above goal, the program was divided into five areas:

- (1) Define mechanical dimensions of the disk-ring elements consistent with machine practices.
- (2) Obtain and measure disk-ring elements to determine the distribution of mechanical dimensions.
- (3) Define disk dimensions required using mathematical models for mechanical filters.
- (4) Compare the results of (2) and (3).
- (5) Build and test complete ring coupled filters.

2. ABSTRACT

Work performed under the contract has shown that machined disk-ring elements, because of present day machining tolerance, are not suitable for manufacturing mechanical filters having stringent bandwidth requirements.

3. FACTUAL DATA

3.1 Integral Disk-Ring Elements

Machined disk-ring elements (Figure 1) were received and inspected using high-powered microscopic and comparator type instruments. Distribution of the three most critical dimensions, ring outside diameter, ring thickness and ring height, for the parts of Figure 1, is shown in Figures 2, 3 and 4. Tolerances were generally met with the exception of ring height, which varied $\pm .002$ " about a mean. As a result of conferences with our vendors and mechanical engineers, a practical limit on ring tolerances was established at $\pm .0005$ ".

In order to predict the effect of variations in ring parameters on bandwidth, a study was made of the mechanical filter's analogous electrical circuit (see Appendix 6.1). Through the study, it was learned that for ring tolerances of $\pm .0005$ ", bandwidth could vary as much as $\pm 13.2\%$. The allowable variation in bandwidth, to meet the sideband specification (CPN 526-9445-00), was found to be less than $\pm 6\%$, which corresponds to ring tolerances of $\pm .0002$ ".

Bandwidths of epoxy bonded disk-ring element pairs (Figure 1) varied approximately $\pm 20\%$, which was a slightly smaller variation than predicted ($\pm 26.4\%$) for tolerances of $\pm .001$ ". Response curves for five epoxy bonded filters, using the elements of Figure 1, are shown in Figures 7 through 16.

Filters E-1 and E-2 were four disk filters while E-3 through E-5 were five disk filters. Figures 17 and 18 are response curves for a five disk conventional disk and wire edge-coupled filter having approximately the same bandwidth and center frequency as the ring coupled filters. A comparison of spurious plots between the edge-coupled filter and the various ring-coupled filter shows the advantage of the ring coupling technique in reducing spurious. This effect is especially noticeable on the high frequency side of the passband.

Disk-ring elements (Figure 5) were ordered having the coupling ring on one side only. Construction of this type simplified tuning of the disks to the desired frequency and epoxy bonding the elements together. These elements were received with only a few days remaining in the contract and, therefore, were inspected on a sample basis. Sample inspection indicated that tolerances were generally met. These indications were also reflected in the small variation in bandwidth ($\pm 9.5\%$) of several epoxy bonded disk pairs shown in Table I. Response curves for a five disk epoxy bonded filter, using the elements of Figure 5, are shown in Figures 19 and 20.

TABLE I
BANDWIDTHS FOR EPOXY BONDED DISK
PAIRS USING THE ELEMENTS OF FIGURE 5

<u>Pair</u>	<u>Bandwidth (KC)</u>
1	2.07
2	2.04
3	2.02
4	1.99
5	1.99
6	1.85
7	1.75
8	1.71
9	1.81

3.2 Separate Disks and Rings

A method of reducing ring tolerances was investigated by using the "A" nickel tubing of Figure 6 as the coupling ring. Bandwidths of several epoxy bonded disk pairs varied less than $\pm 7\%$ about a mean, thus demonstrating the much smaller dimensional tolerances associated with the tubing. Three epoxy bonded filters were constructed. Filter ER-1 (Figures 21 and 22) was a five disk filter while ER-2 and ER-3 (Figures 23 through 26) were eight disk filters. Bandwidths were somewhat wider than filters made from integral disk-ring elements due to the different values of Youngs modulus for Ni-Span "C" and "A" nickel. In the eight disk filters the loss of disk Q, due to epoxy, becomes apparent in the "rounding" of the passband edges.

A technique employing solder to bond disks and rings was also studied. In this technique a small groove, with a mean diameter equal to that of the coupling ring, was

machined on the surface of the disk to be bonded and filled with solder. To make disk pairs, two such disks and the ring of Figure 6 were positioned in a jig and placed in an oven, thus melting the solder and forming a bond between disks and ring. Bandwidths of several disk pairs varied $\pm 13.6\%$ about a mean. These pairs, while less consistent in bandwidth, were stronger and more producible than epoxied pairs using the same elements. The increased bandwidth variation in solder bonded pairs must have been caused by bonding inconsistencies because the same type of coupling ring ("A" nickel tubing) was used in both cases. Response curves for six solder bonded filters are shown in Figures 27 through 38. All filters had five disks with the exception of SR-4 (Figures 33 and 34) which used eight disks. Some fabrication problems exist as evidenced by spurious responses in the passband and passband edges (see Figure 29 for example). To alleviate the problem, further work needs to be done in varying the groove width and depth, trying different solder compositions, etc.

One solder bonded filter (SR-3, Figures 31 and 32) was encased, subjected to 20 G's vibration (Paragraph 2.2 of 526-9430/9444-00) and 100 G's shock (Paragraph 2.3 of 526-9430/9444-00) and showed no measurable change in electrical characteristics subsequent to the tests. During vibration, all amplitude modulation, in the frequency range of 55 cps

to 2000 cps, was attenuated by greater than 60 db. While no epoxy bonded filters were given shock and vibration tests under this contract, past filters have withstood 50 G's shock and 10 G's vibration with mechanical failure occurring at 20 G's vibration.

4. CONCLUSIONS

With tolerances on machined disk-ring elements held to a minimum, bandwidth variation could still exceed that allowable to meet the sideband specification. ^{for these filters} Consequently, a low yield rate and high costs would be expected for this type of filter.

Epoxy bonded filters employing separate disks and rings would approach the necessary bandwidth consistency. However, it is doubtful that any epoxy bonded filter, using present bonding techniques, would withstand the shock and vibration requirements. Also, the loss of disk "Q", due to epoxy, would hinder the filter's passband response.

Solder bonded filters using separate disks and rings, while capable of withstanding shock and vibration, would exhibit more bandwidth variation than acceptable to meet the sideband specification. However, some improvement in bandwidth consistency should be possible ^{by applying the bonding technique} because it is known that dimensional tolerances account for only half of the total bandwidth variation experienced. The other half must be due to bonding techniques, which should be capable of improvement.

Thus, through solder bonding techniques, a very rigid and exceedingly strong mechanical filter has ^{been} developed. This filter exhibits considerable reduction in spurious responses over conventional edge-coupled mechanical filters. With some additional development, this filter should be capable of mass production to a specification with less critical requirements than the sideband specification.


5. RECOMMENDATIONS

As demonstrated by the preceding work, solder bonded filters using separate disks and rings are exceptionally strong and comparatively easy to build. It is, therefore, recommended that any further study be concentrated in this area. Such a study should include an investigation of the following fabrication problems:

- (1) Groove width and depth
- (2) Solder composition
- (3) Jigging

In addition, design goals should be changed to encompass a filter such as the frequency selectors (CPN 526-9430/9444-00) where bandwidth tolerances are not as critical.

.005 RAD MAX

 $.030 \pm .001$ $.030 \pm .001$ $.071 \pm .001$ $.350 \pm .0002$ $.125 \pm .001$ $.113 \pm .001$ 

MATERIAL: NI - SPAN C

FIGURE 1

UNLESS OTHERWISE SPECIFIED
DIMENSIONS ARE IN INCHES
TOLERANCES ON
FRACTIONS DECIMALS ANGLES
 $\pm 1/64$ $\pm .005$ $\pm 1^\circ$

CODE IDENT
NO
13499

SIZE

A

37-1775-008

SCALE NONE

WT

SHEET

FREQUENCY DISTRIBUTION ANALYSIS SHEET

FIGURE 2

TRIMON

[illegible]


STATISTICAL QUALITY CONTROL FREQUENCY DISTRIBUTION ANALYSIS SHEET

FIGURE 3

PART NAME		DEPARTMENT OF SUPPLY		DATE	
Thickens of Coupling Ring (inches)		CLASSIFICATION		ANALYST	
DISTRIBUTION TYPE		PERCENTAGE OVER		PERCENTAGE UNDER	
1	TALLY	2	5	6	
X		1	Acc. 2	5+4	
.0040	I	1	1	26	
.0042	I	1	3	79	
.0044		0	4	105	
.0046		0	4	105	
.0048	III IIII	12	16	421	
.0050	III IIII	11	39	103	
.0052	III IIII IIII	16	66	174	
.0054	III IIII IIII IIII	19	101	266	
.0056	III IIII IIII	14	134	353	
.0058	III IIII IIII IIII	22	170	447	
.0060	III IIII IIII IIII	18	210	552	
.0062	III IIII IIII IIII IIII	28	256	674	
.0064	III IIII IIII	16	300	789	
.0066	III I	6	322	847	
.0068	III IIII	11	339	892	
.0070	III IIII	11	361	950	
.0072	II	2	374	984	
.0074	I	1	377	992	
.0076		0	378	995	
.0078	I	1	379	997	
3 TOTAL		190			
4 TOTAL		380			
MODERATE CAPABILITY					

STATISTICAL QUALITY CONTROL FREQUENCY DISTRIBUTION ANALYSIS SHEET

FIGURE 4




REVISIONS

.005 RAD MAX

.060 ± .001

.060 ± .001

.071 ± .001



MATERIAL: NI-SPAN "C"

QTY RECD SYM ITEM GOV IDENT NO. COLLINS PART NO.

DESCRIPTION

UNLESS NOTED

DIM ARE IN INCHES
FRACTION DEC ANGLES
± 1/32 .008 ± 1°

DRAWN DL BISE 3-25-64

CHECK

ENG

APPR

DISK-RING

FIGURE 5

INFORMATION SCIENCE CENTER



NEWPORT BEACH, CALIF.

37-1775-00F



CODE IDENT : 95105

WT :

SCALE : NONE


SHT 1 OF 1


REVISIONS



NOTE:
REMOVE ALL BURRS AND
SHARP EDGES

MATERIAL: "A" NICKEL

QTY RECD	SYM	ITEM	GOV IDENT NO.	COLLINS PART NO.	DESCRIPTION
UNLESS NOTED					<p>INFORMATION SCIENCE CENTER</p>  <p>NEWPORT BEACH, CALIF.</p> <p>37-1775-006</p>
DIM ARE IN INCHES					
FRACTION DEC ANGLES					
± 1/32 .008 ± 1°					
DRAWN D.L. BISE 4-1-64					
CHECK					<p>COUPLING RING</p> <p>FIGURE 6</p>
ENG					
APPR					
CODE IDENT : 95105			WT :		SCALE : NONE
					SHT 1 OF






FIGURE 9

FILTER E-2

TERMINATION


Input 18 K Ω

130 pF

Output 18 K Ω

140 pF

Parallel-tuned







FIGURE 11
FILTER E-3
TERMINATION
Input 22 K Ω
130 pF
Output 33 K Ω
130 pF
Parallel tuned







FIGURE 13
FILTER E-4
TERMINATION
Input 36 K Ω
100 pf
Output 22K
110 pf
Parallel tuned






FIGURE 15
FILTER E-5
TERMINATION
Input 39K Ω 125pF
Output 39K Ω 130pF
Parallel tuned




FIGURE 16
FILTER E-5
SPURIOUS PLOT




FIGURE 17

FILTER W-1

TERMINATION

Input 39K Ω 105pF

Output 39K Ω 105pF

Parallel tuned





FIGURE 18
FILTER W-1
SPURIOUS PLOT






FIGURE 20
FILTER E'-1
SPURIOUS PLOT




FIGURE 21
FILTER ER-1

TERMINATION

Input 20K Ω

105 μ f

Output 27K Ω

110 μ f

Parallel tuned




FIGURE 22
FILTER ER-1
SPURIOUS PLOT




FIGURE 23
FILTER ER-2
TERMINATION

Input 27K Ω 105pF
Output 27K Ω 115pF
Parallel tuned






FIGURE 24
FILTER ER-2
SPURIUS PLOT








FIGURE 27
FILTER SR-1
TERMINATION
INPUT 51 K Ω
110 P F
OUTPUT 56 K Ω
105 P F
PARALLEL TUNED




FIGURE 28

FILTER SR-1
SPURIOUS PLOT




FIGURE 29
FILTER SR-2
TERMINATION

Input 15 K Ω
120 pF

Output 15 K Ω
115 pF
Parallel Tuned




FIGURE 30
FILTER SR-2
SPURIOUS PLAT




FIGURE 31

FILTER SR-3

TERMINATION

Input 27 K Ω


117 pF

Output 27 K Ω

115 pF

Parallel tuned

ATTENUATION (dB)



FREQUENCY (KC)

FIGURE 32
FILTER SR-3
SPURIOUS PLOT




FIGURE 33

FILTER SR-4

TERMINATION

INPUT 27K Ω 80PF

OUTPUT 27K Ω 80PF

PARALLEL TUNED




FIGURE 34
FILTER SR-4
SPURIOUS PLOT




FIGURE 35


FILTER SR-5


TERMINATION

INPUT 30 KΩ
114 pF

OUTPUT 27 KΩ
120 pF

Parallel tuned









FIGURE 38
FILTER SR-6
SPURIOUS PLOT



6. APPENDICES

- 6.1 Parameter Study of Mathematical Model for Mechanical Filters
- 6.2 Sideband Filter Specification 526-9445-00
- 6.3 Frequency Selector Filter Specification 526-9430/9444-00

6.1 Parameter Study of Mathematical Model for Mechanical Filters

In order to predict the effect of variations in ring parameters on bandwidth, it was necessary to investigate the mechanical filters analogous electrical circuit. In the circuit of Figure I, inductance is analogous to a spring and capacitance is analogous to a mass. If this circuit is designed on an image parameter basis, the element values are defined as follows:

$$(1) \quad L_R = \frac{2 R_n}{\omega_1 + \omega_2} = \frac{2 R_n}{2\omega_1 + BW}$$

$$(2) \quad L_D = \frac{R_n BW}{2\omega_1^2}$$

$$(3) \quad C_D = \frac{2}{R_n BW}$$

Where:

L_R = equivalent inductance of the coupling ring

L_D = equivalent inductance of the disk

C_D = equivalent capacitance of the disk

ω_1 = lower cutoff frequency

ω_2 = upper cutoff frequency

$BW = \omega_2 - \omega_1$

R_n = design impedance

Substituting the expression for R_n obtained from (3) into (1) we find:

$$(4) \quad L_R = \frac{4}{C_D(2\omega_1 + BW)BW}$$

The coupling inductance L_R in the electrical analogy can also be expressed in terms of the mechanical dimensions:

$$(5) \quad L_R = \frac{l_R}{A_R E}$$

Where:

A_R = cross sectional area of coupling ring

E = Youngs Modulus

l_R = total length of coupling ring (spacing between disks)

From Figure II, it can be shown that:

$$(6) \quad A_R = \pi T_R (D_R - T_R)$$




Figure II Cross Sectional View of Coupling Ring

For $D_R \gg T_R$

$$(7) \quad A_R \cong \pi T_R D_R$$

Combining equations (4), (5) and (7)

$$(8) \quad \frac{4}{C_D(2\omega_1 + BW)BW} \cong \frac{l_R}{\pi E T_R D_R}$$

Figure III shows a plot of equivalent mass versus normalized distance from the center of a disk of radius a , vibrating in a two nodal circle flexural mode.⁽¹⁾ The two points of discontinuity represent the nodal circles where the velocity is zero. The coupling ring is placed at:

$$\frac{r}{a} = \frac{.119}{.350} = .340$$

For very small variations in r ($\Delta r \leq .001$ ") we can approximate the curve with a straight line in the region of interest.

$$(9) \quad C_D = M_{eq} \cong 246 D_R - 27.4 \quad \text{for } .124" \leq D_R \leq .126"$$

Substituting (9) into (8) and letting $K = 4\pi E$ we have:

$$(10) \quad \frac{K}{(246 D_R - 27.4) (2\omega_1 + BW) BW} \cong \frac{l_R}{T_R D_R}$$

To find $\frac{dBW}{BW}$ (the fractional change in bandwidth) from equation

(10), treat l_R as the dependent variable and write:

$$(11) \quad l_R \cong \frac{K T_R D_R}{(246 D_R - 27.4) (2\omega_1 + BW) BW}$$

With l_R expressed as a function of three independent variables we can find the total derivative of l_R as a function of the partial derivatives of l_R and the total derivatives of the independent variables.

$$(12) \quad dl_R = \frac{\partial l_R}{\partial T_R} dT_R + \frac{\partial l_R}{\partial D_R} dD_R + \frac{\partial l_R}{\partial BW} dBW$$

Taking the partial derivatives and dividing both sides of the equation by l_R we have:

(1) Roshan Lal Sharma "Axially Symmetric Vibrations of a Thick Circular Disk" Collins Radio Company (unpublished)

$$(13) \quad \frac{dl_R}{l_R} \cong \frac{dT_R}{T_R} - \frac{27.4}{246 D_R - 27.4} \frac{dD_R}{D_R} - \frac{2\omega_1 + 2BW}{2\omega_1 + BW} \frac{dBW}{BW}$$

Solving equation (13) for $\frac{dBW}{BW}$ and letting $BW = 2\pi \cdot 3 \text{ KC}$, $\omega_1 = 2\pi \cdot 455 \text{ KC}$ and $.124" \leq D_R \leq .126"$ we find:

$$(14) \quad \frac{dBW}{BW} \cong \frac{dT_R}{T_R} - 8 \frac{dD_R}{D_R} - \frac{dl_R}{l_R}$$

We now have an expression for the fractional change in bandwidth in terms of the fractional changes in ring dimensions. Considering dimensional tolerances of $\pm .001$, the possible variation in bandwidth would be:

$$\frac{dBW}{BW} (\%) \cong \pm \left[\frac{.001}{.006} + 8 \frac{(.001)}{.125} + \frac{.002}{.060} \right] 100 = \pm 26.4\%$$

If all ring tolerances were reduced to a machining practical limit of $\pm .0005$ ", the possible variation in bandwidth would be:

$$\frac{dBW}{BW} (\%) \cong \pm 13.2\%$$





FIGURE I

MECHANICAL FILTER ELECTRICAL ANALOGY



6.2 Sideband Filter Specifications 526-9445-00

APPLICATION		QTY REQD		REVISIONS			
NEXT ASSY	USED ON	NEXT ASSY	FINAL ASSY	SYM	DESCRIPTION	DATE	APPROVAL
				A	CD-00469; Added P/N 526-9445-021.	26 OCT 1962	
				B	CD-00447; Changed location of decal on dwg. sheet 5.	1 FEB 1963	<i>TDH</i> 2-20-63
				C	REV. PARAGRAPH UNDER 526-9445-011, CD 02897	10 OCT 1963	<i>TDH</i>

Description: This specification covers the requirements of a 455 KC carrier, upper sideband selector, mechanical.

REFERENCE ONLY

JUN 25 1964

1	SA	1	526-9445-003	MECH. FILTER			
QTY REQD	SYM	ITEM NO.	PART NUMBER	PART NAME	CODE IDENT	GOV'T IDENT NO.	SPECIFICATION

LIST OF MATERIALS OR PARTS LIST

UNLESS OTHERWISE SPECIFIED		DWG BY <i>R. Muret</i>	FILTER, MECHANICAL FL455Z-10	COLLINS RADIO COMPANY NEWPORT BEACH CALIF CODE IDENT NO 95105	
DIMS ARE IN IN. TOLERANCES ON		CHK BY R. Muret			
FRAC DEC ANGLES		ENGR <i>(W. Bond)</i>			
MATERIAL -		ENGR L. Viles			
FINISH -		APPROVE.	SCALE	DWG SIZE	526-9445-00
		DATE 11 May 1962 WRITTEN	WT	A	SHEET 1 OF 5

*When part number appears as 526-9445-009, Military Inspection is required.

When part number appears as 526-9445-011, the requirements shall be changed as follows:

- (a) Paragraph 1.2., the 1.5 db at -25°C is changed to read 1.5 db at 0°C , and *THE 1.7 db AT $\pm 85^{\circ}\text{C}$ IS CHANGED TO READ 1.7 db AT $+60^{\circ}\text{C}$.*
- (b) Paragraph 1.3.2., the -25°C is changed to read 0°C and $+60^{\circ}\text{C}$, paragraph 1.3.3. is deleted.
- (c) Paragraphs 2.2, 2.3. and 2.4 are deleted.

When part number appears as 526-9445-021, the requirements shall be changed as follows:

- (a) Para. 1.2. The peak to valley ratio shall not exceed 3.0 db from 0°C to $+50^{\circ}\text{C}$, other requirements shall be deleted.
- (b) Para. 1.3.1. The frequency shall be 455.12 max. and 457.80 min. at 3.0 db down. Other requirements shall not change.
- (c) Para. 1.3.2. Temperature shall be changed from -25°C to 0°C . The frequency shall be 455.18 max. and 457.80 min. at 3.0 db down. Other requirements shall not change.
- (d) Para. 1.3.3. Temperature shall be changed from $+85^{\circ}\text{C}$ to $+50^{\circ}\text{C}$. The frequency shall be 455.18 max. and 457.80 min. at 3.0 db down. Other requirements shall not change.
- (e) Para. 1.4. The insertion loss shall not exceed 10 db.
- (f) Para. 1.5. The spurious response shall not exceed 35 db from 400 kc to 500 kc. Other requirements shall be deleted.
- (g) Para. 1.6. The -25°C and $+85^{\circ}\text{C}$ requirements shall be changed to 0°C and $+50^{\circ}\text{C}$.
- (h) Delete paragraphs 2.2, 2.3 and 2.4.

REFERENCE ONLY

JUN 25 1964

1. ELECTRICAL REQUIREMENTS.-

- 1.1 Impedance.-- The filters shall be used and tested in a circuit that presents 600 ohms resistive input and output impedance. The filters will be series resonated, no limits being placed on the value of resonating capacity needed. (Nominal value 140 uuf.) The resonating capacity shall not be varied when running temperature tests.

UNLESS OTHERWISE SPECIFIED DIMENSIONS ARE IN INCHES TOLERANCES ON FRACTIONS DECIMALS ANGLES $\pm 1/64$ $\pm .005$ $\pm 1^{\circ}$	CODE IDENT NO.	SIZE	526-9445-00*
	95105	A	
	SCALE NONE	WT	SHEET 2

- 1.2 Peak to valley ratio.- The peak to valley ratio in the passband shall not exceed:

1.0 db at +25°C
1.5 db at -25°C
1.7 db at +85°C

- 1.3 Selectivity.- The bandpass characteristics shall be as follows:

- 1.3.1 +25°C

<u>DB Down From Peak Response</u>	<u>Frequency</u>	<u>Frequency Tolerance</u>
65	453.34	Min.
3	455.00	Min.
1.2	455.12	Max.
1.2	457.80	Min.
3	458.30	Max.
65	459.67	Max.

- 1.3.2 -25°C

<u>DB Down From Peak Response</u>	<u>Frequency</u>	<u>Frequency Tolerance</u>
65	453.34	Min.
3	455.00	Min.
1.5	455.18	Max.
1.5	457.80	Min.
3	458.30	Max.
65	459.67	Max.

REFERENCE ONLY

JUN 25 1964

- 1.3.3 +85°C

<u>DB Down From Peak Response</u>	<u>Frequency</u>	<u>Frequency Tolerance</u>
65	453.30	Min.
3	455.00	Min.
1.7	455.18	Max.
1.7	457.00	Min.
3	458.30	Max.
65	459.67	Max.

- 1.4 Insertion loss.- The insertion loss shall not exceed 6 db in the passband. The insertion loss is the difference in voltage (db) across the load with the filter in the circuit and the filter (including capacity) out of the circuit.

UNLESS OTHERWISE SPECIFIED DIMENSIONS ARE IN INCHES TOLERANCES ON FRACTIONS DECIMALS ANGLES ±1/64 ±.005 ±1°	CODE IDENT NO.	SIZE	526-9445-00
	95105	A	
SCALE NONE	WT	SHEET 3	

- 1.5 Spurious response.- Any response outside the normal passband shall not exceed the following limits when measured from the level of maximum response within the passband at 25°C.

From 400 KC to 405 KC	65 db attenuation
From 405 KC to 430 KC	30 db attenuation
From 430 KC to 440 KC	50 db attenuation
From 440 KC to 453.34 KC	65 db attenuation
From 459.67 to 475 KC	65 db attenuation
From 475 KC to 485 KC	60 db attenuation
From 485 KC to 500 KC	65 db attenuation

- 1.6 Passband.- The passband is defined as 455.12 KC to 457.80 KC at +25°C and 455.18 KC to 457.80 KC at -25°C and +85°C.

2. ENVIRONMENTAL REQUIREMENTS.- (Not included in Para. 1.)

- 2.1 Low temperature storage.- The filter shall be fully operable in its normal temperature range after -80°F exposure for 24 hours.
- 2.2 Vibration.- The filters shall be tested in accordance with Method 204, Test Condition C, Part 2 of MIL-STD-202A dated October 24, 1956, with the exception that the peak acceleration shall be 20 G and that they are to be vibrated in any one direction perpendicular to the length of the filter.
- 2.3 Vibration modulation.- During vibration, with a 456.5 KC input signal of amplitude such that the filter output is 1 volt RMS, the output shall be monitored to detect modulation. If modulation appears on the test signal, its amplitude shall not exceed the following limits referenced to a 1 volt RMS, RF, 100 percent modulated signal.

From 55 cps to 800 cps	50 db attenuation
From 800 cps to 1,000 cps	35 db attenuation
From 1,000 cps to 2,000 cps	30 db attenuation

- 2.4 Shock.- The filters shall be capable of withstanding shock, 100 G for a seven (7) millisecond duration, consisting of five (5) blows in each of two (2) directions, in each of three (3) perpendicular planes. This test shall be performed in accordance with Method 202A of MIL-STD-202A, dated 24 October 1956, and the filters shall exhibit no permanent degradation of electrical performance.

REFERENCE ONLY

3. RECOMMENDED OPERATING PARAMETERS.-

JUN 25 1964

- 3.1 Signal input voltage.- 0 to 1 volt RMS.
- 3.2 Direct current.- Shunt feed is necessary to eliminate DC current in transducer coils. DC current in transducer coils will alter the electrical characteristics of Para. 1.

UNLESS OTHERWISE SPECIFIED DIMENSIONS ARE IN INCHES TOLERANCES ON FRACTIONS DECIMALS ANGLES ±1/64 ±.005 ±1°	CODE IDENT NO.	SIZE	526-9445-00
	95105	A	
SCALE	NONE	WT	SHEET 4

4. MECHANICAL REQUIREMENTS.-


- 4.1 Construction.- Hermetically sealed.
- 4.2 Case.- Cartridge brass; see Sheet 4 for dimensional details.
- 4.3 Finish.- Nickel plate, Type VI, Class 2, in accordance with the latest version of QQ-N-290.
- 4.4 Nameplate.- A suitable metal foil or decalcomania nameplate shall be attached to the filter and shall include the following data:
 Collins Type
 Serial Number or Date Code Stamp
 Collins Part Number
 Silk screening or rubber stamped identification data may be used in lieu of a nameplate. The nameplate shall remain firmly attached and legible after subjection to the environmental tests of Para. 3.

5. PRODUCTION TEST REQUIREMENTS AT COLLINS RADIO COMPANY.-

- 5.1 Production inspection tests.- All units shall be tested for the following:
1. Visual Inspection for mechanical requirements and workmanship.
 2. Electrical requirements of Para. 1.
 3. Environmental requirements of Para. 2.

REFERENCE ONLY

JUN 25 1964



UNLESS OTHERWISE SPECIFIED DIMENSIONS ARE IN INCHES TOLERANCES ON FRACTIONS DECIMALS ANGLES $\pm 1/64$ $\pm .005$ $\pm 1^\circ$	CODE IDENT NO.	SIZE	526-9445-00	
	95105	A		
SCALE NONE		WT	SHEET 5	

6.3 Frequency Selector Filter Specifications 526-9430/9444-00

NOTICE: WHEN GOVERNMENT DRAWINGS, SPECIFICATIONS, OR OTHER DATA ARE USED FOR ANY PURPOSE OTHER THAN IN CONNECTION WITH A DEFINITE RELATED GOVERNMENT PROCUREMENT OPERATION, THE UNITED STATES GOVERNMENT HEREBY INCURS NO RESPONSIBILITY FOR ANY OBLIGATION WHATSOEVER, AND THE FACT THAT THE GOVERNMENT MAY HAVE FORMULATED, FURNISHED, OR IN ANY WAY SUPPLIED THE SAID DRAWINGS, SPECIFICATIONS, OR OTHER DATA IS NOT TO BE REGARDED BY IMPLICATION OR OTHERWISE AS IN ANY MANNER LENDING THE CREDIT OR AUTHORITY OF THE GOVERNMENT TO ANY PERSON OR CORPORATION, OR CONVEYING ANY RIGHTS OR PERMISSION TO MANUFACTURE, USE, OR SELL ANY PATENTED INVENTION THAT MAY IN ANY WAY BE RELATED THERE TO.

REVISIONS

SYM	DESCRIPTION	DATE	APPROVED

REFERENCE ONLY

Description: MECHANICAL FILTER
f_c KC CENTER FREQUENCY SELECTOR

JUN 25 1964

COLLINS RADIO CO., NEWPORT BEACH, CALIF. 926

VENDOR

CODE IDENT. NO.

VENDOR P. N.

CLASS 2B

CAL CHANGE 3 MAY 1962

SOURCE CONTROL DRAWING

ENGRG 082-0123/0137-526
PN 082-0160/0174-526

NAME

DATE

PREP BY Kirtley J. 26 April 1962

CHK BY E. N. Murt 4-26-62

PROJ CHK C. W. Ford 9/26/62

PROJ ENGR T. D. U. 4-26-62

DWG DATE 11 May 1962

COLLINS RADIO COMPANY
NEWPORT BEACH, CALIFORNIA

FILTER, MECHANICAL

CODE IDENT
NO.

95105

SIZE

A

* 526-9430/9444-00

SCALE NONE

WT

SHEET 1 of 4

REV

2.2.1 Vibration Modulation: During vibration, with a center frequency (f_c) input signal of amplitude such that the filter output is 1 volt RMS, the output shall be monitored to detect modulation. If modulation appears on the test signal, its amplitude shall not exceed the following limits referenced to a 1 volt RMS, RF, 100 percent modulated signal.

From 55 cps to 800 cps	40 db attenuation
From 800 cps to 1,000 cps	35 db attenuation
From 1,000 cps to 2,000 cps	30 db attenuation

2.3 Shock: The filters shall be capable of withstanding shock, 100 G for eleven (11) millisecond duration, consisting of five (5) blows in each of two (2) directions in each of three (3) mutually perpendicular planes. The test shall be performed in accordance with Method 202A, of MIL-STD-202A, dated 24 October 1956, and the filters shall exhibit no permanent degradation of electrical performance.

REFERENCE ONLY

3. MECHANICAL REQUIREMENTS:

JUN 25 1964

3.1 Construction: Hermetically sealed.

3.2 Case: Cartridge brass; see figure for dimensional details.

3.3 Finish: Nickel plate, Type VI, Class 2, in accordance with the latest version of QQ-N-290.

3.4 Nameplate: A suitable metal foil or decalcomania nameplate shall be attached to the filter and shall include the following data:

Collins Type

Serial Number or Date Code Stamp

Collins Part Number

Silk screening or rubber stamped identification data may be used in lieu of a nameplate. The nameplate shall remain firmly attached and legible after subjection to the environmental tests of Para. 3.

4. PRODUCTION TEST REQUIREMENTS AT COLLINS RADIO COMPANY:

4.1 Production Inspection Tests: All units shall be tested for the following:

1. Visual Inspection for mechanical requirements and workmanship.
2. Electrical Requirements of Para. 1.
3. Environmental Requirements of Para. 2.


UNLESS OTHERWISE SPECIFIED DIMENSIONS ARE IN INCHES TOLERANCES ON FRACTIONS DECIMALS ANGLES $\pm 1/64$ $\pm .005$ $\pm 1^\circ$	CODE IDENT NO. 95105	SIZE A	* 526-9430/9444-00
	SCALE NONE	WT	SHEET 3 of 4

TABLE I

<u>f_c (KC)</u>	<u>Collins Part Number</u>	<u>Collins Type No.</u>
459.74	526-9430-00	FL459Y-20
464.48	526-9431-00	FL464Y-20
469.22	526-9432-00	FL469Y-20
473.96	526-9433-00	FL473Y-20
478.70	526-9434-00	FL478Y-20
483.44	526-9435-00	FL483Y-20
488.18	526-9436-00	FL488Y-20
492.92	526-9437-00	FL492Y-20
497.66	526-9438-00	FL497Y-20
502.40	526-9439-00	F502Y-20
507.14	526-9440-00	F507Y-20
511.88	526-9441-00	F511Y-20
516.62	526-9442-00	F516Y-20
521.36	526-9443-00	F521Y-20
526.10	526-9444-00	F526Y-20

REFERENCE ONLY

JUN 25 1964



UNLESS OTHERWISE SPECIFIED
DIMENSIONS ARE IN INCHES
TOLERANCES ON
FRACTIONS DECIMALS ANGLES
 $\pm 1/64$ $\pm .005$ $\pm 1^\circ$

CODE IDENT
NO.
95105

SIZE
A

* 526-9430/9444-00

SCALE NONE

WT

SHEET 4 of 4